cellularline

ISTRBTSHADOWTWSK

Shadow

EN WIRELESS STEREO BLUETOOTH® HEADSET WITH CHARGING CASE

IT AURICOLARI BLUETOOTH® STEREO SENZA FILI CON CUSTODIA DI RICARICA

FR ÉCOUTEURS BLUETOOTH® STÉRÉO SANS FILS AVEC ÉTUI DE CHARGE

DE DRAHTLOSES BLUETOOTH®-STEREO-HEADSET MIT LADEHÜLLE

ES AURICULARES BLUETOOTH® ESTÉREO INALÁMBRICOS CON FUNDA DE RECARGA

RU БЕСПРОВОДНЫЕ СТЕРЕОНАУШНИКИ BLUETOOTH® С ЗАРЯДНЫМ ЧЕХЛОМ

TR YENİDEN ŞARJ KILIFLI KABLOSUZ BLUETOOTH® STEREO KULAK İÇİ KULAKLIKLAR

NL DRAADLOZE STEREO BLUETOOTH® HEADSET MET OPLAADSTATION



EN

Description:

1 MFB button
2 LEDs
3 Charging Case
4 Led Charging Case
5 MicroUSB charging socket
6 MicroUSB charging cable

IT

Descrizione:

1 Tasto MFB
2 Led
3 Charging Case
4 Led Charging Case
5 Presa di ricarica MicroUSB
6 Cavo di ricarica MicroUSB

EN - PRELIMINARY OPERATIONS

Recharge Charging Case: Charging Case is equipped with internal battery and allows for the charging of devices even without direct power. It is therefore necessary to charge the Charging Case before recharging the batteries of the devices.

Insert the charging cable into any USB port and connect the MicroUSB connector to the recharge socket of the device (5), the LED (4) will light up red and will switch off when charging is complete.

Once the charging is complete, disconnect the Charging Case from the power supply.

Charging the earbuds: insert the devices into their housings and close the Charging Case, the charging will be activated automatically. The red LED (2) indicates charging in progress, when charging is complete, the LED (2) will switch off.

Connection of TWS devices: remove the devices from the charging cradle, both devices will automatically turn on and the LEDs (2) will start flashing blue and after a few seconds they will connect to each other.

Pairing with the phone: once the TWS connection has been established, the LED (2) of one of the two earbuds will flash red – blue, indicating that the pairing mode is active. Follow the instructions on the phone display to find the device.

Activate your phone's Bluetooth to search for devices and select SHADOWS when it is detected.

Note: During conversations, the audio will be transmitted on a single earbud.

Connecting the phone with one of the earbuds: switch off the earbuds and hold down the MFB button (1) on one of the devices until the red/blue alternating LED flashes (2), about 6 seconds.

Activate your phone's Bluetooth to search for devices and select SHADOWS when it is detected.

The earbud LED will flash blue to indicate that it has been paired, if the pairing operation has failed, turn off the earbud and try again.

If you want to connect the second earbud, just turn it on, after 3 seconds it will connect automatically to the other device.

Pairing the earbud with the second phone (multipoint function):

Disable Bluetooth on the first phone

To establish the connection with the second telephone, refer to the paragraph "pairing a single earbud with the phone”.

Once the connection is established, reactivate the Bluetooth on the first phone and select SHADOWS if the reconnection does not occur automatically.

NOTE: in the multipoint mode, the connection between the two earbuds cannot be re-established
Turning on: hold down the MFB button (1) until the blue LED starts to flash (about 3 seconds).
Turning off: hold down the MFB button (1) until the red LED starts to flash (about 3 seconds)
Warning: if the headset or the telephone have been turned off or taken out of range, you may need to use the telephone menu to reconnect them or simply the MFB (1) as if you were answering a call.

USE OF THE DEVICE:
Answer a call: Briefly press the MFB button (1).
End a call: Briefly press the MFB button (1).
Play/Pause: press the MFB button (1)
Speaker volume adjustment: To adjust the volume while a conversation is under way, use the volume buttons on the phone.
Low battery indicator: the flashing red LED indicates the battery capacity is low.

EARBUDS TECHNICAL SPECIFICATIONS:
Bluetooth: v4.1
Profiles supported Headset – Handsfree – A2DP - AVRCP
Range: 10mt
Bluetooth Frequency Range: 2.4GHz-2.48GHz
Battery Voltage: 3.7V
Battery Capacity: 45mAh X 2
Charging Case battery capacity: 300mAh
MicroUSB port Voltage (V): 5V
MicroUSB port current (A): 260mAh
ERP power: 2.5mmW
Stand by Time: 80 hours
Talk Time: 2.5 hours
Play Time: 2.5 hours
Recharge earbuds: about 2 hours
Recharge Charging Case: about 2 hours
Weight: 38g